

Datasheet

U_{P0}/S₀ Adapter



Converts from 2-core U_{P0} to 4-core S₀



- 1 internal S₀ port (PTMP connection, DSS-1) via 2-core connection
- Simple installation using Western plugs, a fixed installation alternatively via screw terminals
- 2 RJ-45 plugs for ISDN system telephones from the COMfortel[®] series and standard ISDN devices
- LEDs for displaying operational states
- Can be operated as a desktop or wall-mounted device

Your advantages in detail

With the U_{P0}/S₀ adapter, ISDN system telephones from the COMfortel series and standard ISDN devices can

be adapted to the U_{P0} port of an ICT system. Enables "old" 2-core cables to be useable for ISDN connections.

do you speak
FONtevo[®]

Features at a glance

FUNCTIONS

- Adapter for connection at a 2-wire- U_{P0} port, transforming to 4-wire S_0 interface
- 1 internal S_0 port with 2 plugs for 2 system or ISDN telephones
- Power supply via the U_{P0} port
- Installation via western plugs, fix installation via screw terminals possible
- LEDs for signalling operating and functional states

TECHNICAL SPECIFICATIONS

- Operating voltage: via the internal U_{P0} port of the ICT system

- Connections: 1 x U_{P0} port for connecting the ICT system, 2 x S_0 port Euro-ISDN (DSS-1), PTMP
- Range of internal S_0 port: approx. 15 m
- Casing material: plastic, grey
- Dimensions (d x h): \varnothing 95 mm x 33 mm
- Weight: approx. 100 g
- Compliance: CE

DELIVERY

- U_{P0}/S_0 Adapter
- U_{P0} connection cable RJ-45/RJ-11 (ca. 4 m)
- Mounting material (screws and dowel)
- User manual

ORDERING INFORMATION

Designation: UP0/S0 Adapter

Article number: 90436

EAN Code: 4019377904367